zenitel

DATASHEET

1007095000

Poste principal industriel

ATEX IIC T6



Description

- Poste principal industriel ATEX haute résistance
- Conçu pour être utilisé avec le serveur AlphaCom Vingtor-Stentofon
- 12 touches résistantes :
  - Bontons d'appel (0-9)
  - PTT pour conversations en mode simplex (M)
  - Touche d'annulation (C)
- Boîtier en acier laqué robuste et résistant aux intempéries
- Combiné de discrétion

www.zenitel.com info@zenitel.com

Last revision date: 2022-08-26 09:27

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

- Haut-parleur externe à prévoir
- Sortie de relais pour le contrôle d'avertisseur d'appel optionnel
- Fonctionnalités de surveillance avancées

L'amplificateur intégré de 10 W nécessite une source d'alimentation pour faire fonctionner un haut-parleur de 8 ou 20 Ohm. Ce poste est connecté au serveur via un câble 3 paires.

Le microphone du combiné est connecté en permanence et permet ainsi de répondre directement aux appels entrants. Le haut-parleur externe ne fonctionne pas lorsque vous utilisez le combiné de discrétion.

Le dispositif d'avertisseur d'appel optionnel est également coupé lorsque vous utilisez le combiné de discrétion. La conversation prend fin dès que vous replacez le combiné sur le poste ou lorsque vous pressez la touche d'annulation (C).

Ce poste est conçu pour des conversations en mode duplex mais vous pouvez également l'utiliser en mode simplex en appuyant sur la touche M ou sur le bouton du combiné.

Pour répondre le mieux à vos besoins et assurer le meilleur fonctionnement, le poste dispose de fonctionnalités de surveillance avancées. Il effectue des tests afin de détecter les possibles erreurs du réseau ou du système ainsi que des tests de tonalité qui vérifient tout le parcours de transmission, microphone et haut-parleur inclus. L'état du poste est transmis à l'AlphaNet ainsi qu'aux systèmes tierce partie utilisant SNMP, Syslog, OPC ou le kit de développement de logiciel Vingtor-Stentofon (SDK).

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

Spécifications

GÉNÉRAL

Dimensions (LxHxP)	215 x 687 x 187 mm
Protection ATEX	ATEX IIC T6
Indice de Protection IP	IP-65
Combiné	Sécurité intrinsèque, avec barrières Zener à l'intérieur du boîtier ATEX
Poids	23 kg
Températures de fonctionnement	De -40°C à +55°C
Amplificateur intégré	10 W
Humidité supportée	De 0% à 95%
Alimentation amplificateur	24-30 VDC
Haut-parleur	Nécessite un haut-parleur externe 8 ou 20 ohms
Matériel	Acier laqué, gris clair
Clavier	12 Boutons : 0-9, M et C
Câble requis	Câble 2 paires pour l'audio + 1 paire 24-30 VDC pour l'amplificateur
Sortie haut-parleur	5 W avec haut-parleur 20 ohms, 10 W avec haut-parleur 8 ohms
Distance du serveur pour l'audio	4,0 km (18 AWG - 0,9 mm), 3,4 km (20 AWG - 0,8 mm), 2,0 km (22 AWG - 0,6 mm)
Longueur de câble	Haut-parleur 8 ohms, 24 VDC, 0,6 mm : 70 m /

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

Longueur de câble	0,8 mm : 100 m / 1 mm : 200 m
	Haut-parleur 8 ohms, 30 VDC, 0,6 mm : 150 m / 0,8 mm : 250 m / 1 mm : 450 m
	Haut-parleur 20 ohms, 24 VDC , 0,6 mm : 150 m / 0,8 mm : 250 m : 1 mm : 400 m
	Haut-parleur 20ohms, 30 VDC, 0,6 mm : 350 m / 0,8 mm : 650 m / 1 mm : 1000 m
Contrôle du dispositif d'appel externe	Contact de relais sans potentiel (3A, 30 VDC)
Connecteur	Bornier à vis
Conformité	CE, FCC Partie 15

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.