zenitel

DATASHEET

1009303001

Carte d'interface audio

AGA



Description

- Interface pour la distribution de 16 canaux audio à destination et/ou en provenance du serveur AlphaCom sous contrôle logiciel
- Fournit 6 canaux de communication birdirectionnelle entre les nœuds d'un système AlphaCom
- Peut être utilisée pour des fonctionnalités spécifiques telles que les conférences Duplex ou le contrôle du volume pour les appels de groupe
- Entrée / sortie 600 Ohm 0 dB isolée par galvanisation via le transformateur
- Terminaison sur carte par cavaliers
- Peut ajouter des sources audio internes et externes à une entrée ou une sortie audio
- 8 canaux pour la communication bidirectionnelle entre les modules d’un système multimodules

www.zenitel.com info@zenitel.com

Last revision date: 2024-05-14 14:51

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company’s Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

- Sensibilité (gain) ajustable individuellement pour tous les canaux
- Connecteur codé pour un positionnement correct dans le module
- Connexion et déconnexion de la carte à chaud

Cette carte est une interface audio généralement utilisée pour la distribution de programmes ou la communication vocale entre modules. Lorsqu'elle est affectée à la distribution de programmes audio, vous pouvez enficher jusqu'à 2 cartes dans les positions 20 et 21.

Affectée à la communication inter-modulaire, chaque carte fournit 8 canaux vocaux par boucle de communication dans un système multi-modules AlphaCom. Chaque module peut accueillir 1 à 3 cartes AGA utilisées à cette fin (positions 22, 23 et 24).

Pour faciliter l’accès, les potentiomètres de réglage de la sensibilité des canaux audio sont situés à l’avant.

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company’s Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

Spécifications

GÉNÉRAL	
Tension	5, 15 VDC
Dimensions (LxHxP)	10 x 230 x 263 mm
Sensibilité (ajustable)	100 mV à 1 V
Gamme de fréquence avec distribution de programmes	40 - 18,5 kHz
Indicateur	LED (rouge / vert / orange)

RÉFÉRENCE	DESCRIPTION	POIDS À L'EXPÉDITION
1009303001	Carte d'interface audio AGA	0,5 kg
1009930300	Kit d'installation pour la distribution de programmes audio (1 par carte)	

www.zenitel.com info@zenitel.com Last revision date: 2024-05-14 14:51

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.