zenitel

DATASHEET



2340130007

SPA-400-V2

Unité de sonorisation rackable

Onboard communication

Description

- Entrée & priorités pour 3 microphones
- Entrée système talk-back
- Entrée système de divertissement
- Entrée PABX avec zones prédéfinies
- Sortie signal 100 V 6 zones
- Entrée pour 2 panneaux d’alarme
- 2x entrées alarme incendie, alarme générale et zone spécifique (pompiers)

www.zenitel.com info@zenitel.com

Last revision date: 2024-06-10 11:35

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company’s Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

- Mise en sourdine de l’alarme pendant la diffusion de messages

La gamme de systèmes de sonorisation et d’alarme générale SPA allie qualité et rentabilité. Le système SPA-V2 est une version améliorée du précédent système installé dans des milliers de navires à travers le monde. Son module de base permet de faire fonctionner un système non redondant. Le SPA-V2 est livré dans un rack 19" contenant une carte mère, un ou plusieurs amplificateurs et des fonctionnalités en option.

Fonctionnalités en option :

- Nombre de microphones et de panneaux d’alarme
- Système double, redondance
- Amplificateurs supplémentaires
- Générateurs d’alarme
- Interface PABX
- Alimentation redondante
- Enregistreur de messages numériques
- Générateur de carillon
- Divertissement
- Sortie pour enregistrement de données vocales

La baie est équipée et câblée selon les spécifications du client à l’issue de la livraison. Système testé et approuvé par la norme EN60945.

Technical Dimensions

false

www.zenitel.com info@zenitel.com Last revision date: 2024-06-10 11:35

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company’s Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

Spécifications

GÉNÉRAL	
Dimensions de rack (LxHxP)	525 x 584 x 525 mm (19” 12 U)
Matériau	Acier peint en noir
Montage	Au sol
Tension d'entrée	Secteur 230 VAC et 24 VDC (110 VAC disponible sur demande)
Connexions	Borniers à vis enfichables pour câbles de max. 2,5 mm2
Câblage	Câble du signal 0,75 mm2, crépine extérieure torsadée
Amplificateur	1x VPA-400, voir la fiche technique dédiée
Sortie	100 V - 400 W
Températures de fonctionnement	De -20°C à +55°C
Humidité supportée	< 95%
Sécurité	EN 60065
Testé conformément à la norme	EN 60945
Dimensions de rack en option	12,16, 20,24,30 et 40 U, 19"

Used With

www.zenitel.com info@zenitel.com Last revision date: 2024-06-10 11:35

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company’s Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.



EA1400

SPA V2 Amplifier 1 x 400W

Référence Produit:
1023131400

www.zenitel.com info@zenitel.com Last revision date: 2024-06-10 11:35

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.