zenitel

DATASHEET



1200300030

INTEGRA-03

Wall Mount PAVA System (3 amps)

- EN 54-16 CERTIFIED
- SELF-CONTAINED WALL MOUNT PAVA SYSTEM
- SIMPLE INSTALLATION WITH MOUNTING FOR BATTERIES
- PRE-INSTALLED WITH 3 AMPLIFIER CHANNELS, EACH CAPABLE OF UP TO 500W @100V
- HIGH QUALITY PROFESSIONAL AUDIO PROCESSING
- 24 BIT 48 kHz AUDIO PROCESSING
- 12 ANALOGUE AUDIO INPUTS & OUTPUTS / 6 IP AUDIO INPUTS
- ON BOARD GENERAL PURPOSE INPUTS & OUTPUTS
- FLEXIBLE CONTROL OPTIONS
- INTEROPERABILITY WITH THE VIPEDIA RANGE

Public Address | Voice Alarm | Commercial Audio | Civil Defence Approval | EN54 | EN 54 Certified

Description

The INTEGRA-03 all-in-one network enabled voice alarm solution is available with three channels of pre-installed amplification, which can be expanded at a later date.

The unit has 12 audio inputs and internal storage for up to 64 recorded messages. With the possibility to upgrade with additional amplifier cards, a single INTEGRA-03 unit can deliver a maximum power of 2000W. With integrated audio-over-IP networking, powerful audio processing, and integrated battery charger and battery mounting shelf all in a compact wall-mount enclosure, INTEGRA provides a complete voice alarm solution for both medium to large centralised and decentralised PAVA systems.

Up to 32 INTEGRA can be linked by IP to enable broadcasts from any location to any combination of zones in large decentralised systems. The network switch (NETWORK-SWITCH-LP01) forms a voice alarm compliant ring network topology and can be easily mounted inside the enclosure.

Any INTEGRA variant and the rack mount equivalent VIPEDIA range interoperate seamlessly.

www.zenitel.com info@zenitel.com Last revision date: 2026-01-20 09:57

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

Specifications

For full details see Documents

POWER	
AC Supply Voltage	230V (+25% / -16%)
AC Supply Frequency	50 / 60 Hz
Quiescent Current (no amplifiers)	525mA
Quiescent Current (per amplifier)	23mA
Maximum Audio Output Power	2000W

Accessories



NETWORK-SWITCH-LP01

PAVA Network Switch - Layer 2

Item Number: 1200571000



LSZDC

PAVA Amplifier Interface Module for the V2000 / INTEGRA

Item Number: 1200540000

BMB01 from datasheet

BMB01

Din Rail Mount I/O Expansion Device

Item Number: 1200550030

from site

D150

PAVA 150W Power Amplifier Module for the V2000 / INTEGRA

Item Number: 1200202150

from site

D500

PAVA 500W Power Amplifier Module for the V2000 / INTEGRA

Item Number: 1200202500

www.zenitel.com info@zenitel.com Last revision date: 2026-01-20 09:57

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.