



1200300030

INTEGRA-03

Wall Mount PAVA System (3 amps)

- ✓ EN 54-16 CERTIFIED
- ✓ SELF-CONTAINED WALL MOUNT PAVA SYSTEM
- ✓ SIMPLE INSTALLATION WITH MOUNTING FOR BATTERIES
- ✓ PRE-INSTALLED WITH 3 AMPLIFIER CHANNELS, EACH CAPABLE OF UP TO 500W @100V
- ✓ HIGH QUALITY PROFESSIONAL AUDIO PROCESSING
- ✓ 24 BIT 48 kHz AUDIO PROCESSING
- ✓ 12 ANALOGUE AUDIO INPUTS & OUTPUTS / 6 IP AUDIO INPUTS
- ✓ ON BOARD GENERAL PURPOSE INPUTS & OUTPUTS
- ✓ FLEXIBLE CONTROL OPTIONS
- ✓ INTEROPERABILITY WITH THE VIPEDIA RANGE

 Public Address Voice Alarm

Commercial Audio



Civil Defence Approval



EN 54 Certified

Description

The INTEGRA-03 all-in-one network enabled voice alarm solution is available with three channels of pre-installed amplification, which can be expanded at a later date.

The unit has 12 audio inputs and internal storage for up to 64 recorded messages. With the possibility to upgrade with additional amplifier cards, a single INTEGRA-03 unit can deliver a maximum power of 2000W. With integrated audio-over-IP networking, powerful audio processing, and integrated battery charger and battery mounting shelf all in a compact wall-mount enclosure, INTEGRA provides a complete voice alarm solution for both medium to large centralised and decentralised PAVA systems.

Up to 32 INTEGRA can be linked by IP to enable broadcasts from any location to any combination of zones in large decentralised systems. The network switch (NETWORK-SWITCH-LP01) forms a voice alarm compliant ring network topology and can be easily mounted inside the enclosure.

Any INTEGRA variant and the rack mount equivalent VIPEDIA range interoperate seamlessly.

Specifications

For full details see Documents

POWER

AC Supply Voltage	230V (+25% / -16%)
AC Supply Frequency	50 / 60 Hz
Quiescent Current (no amplifiers)	525mA
Quiescent Current (per amplifier)	23mA
Maximum Audio Output Power	2000W

Accessories



[BMB01 from datasheet](#)

[BMB01](#)

Din Rail Mount I/O Expansion Device

[from site](#)

[D150](#)

PAVA 150W Power Amplifier Module for the V2000 / INTEGRA

[from site](#)

[D500](#)

PAVA 500W Power Amplifier Module for the V2000 / INTEGRA

NETWORK-SWITCH-LP01

PAVA Network Switch - Layer 2



LSZDC

PAVA Amplifier Interface Module for the V2000 / INTEGRA

page 2/2