

BMB01 from datasheet

1200550030

BMB01

Din Rail Mount I/O Expansion Device

✔ SUPERSEDED BY THE BMB02

Description

The BMB01 is a DIN-rail mountable enclosure, that functions as an input and output contact (I/O) expander specifically designed to enhance the capabilities of Zenitel's PAVA system. This device acts as an extension, augmenting the features of the PAVA System.

The BMB01 connects to a host Audio Router using DC power and a RS485 serial interface, supporting multi-drop communication that can accommodate up to nine units connected in parallel. Typically, the BMB01 is installed inside the PAVA cabinet alongside the host audio router. However, utilizing standard CAT5/6 cable, the expander can be placed externally up to 500 meters away from the host device. Each BMB unit supports: 12 optionally monitored analogue inputs, 12 opto-isolated digital inputs and 12 monitored digital outputs with open collector configuration. The GPIO offers a range of functions including:

- ✔ Program Selection
- ✔ Volume Control
- ✔ Third-party Fault Monitoring
- ✔ Routing Control
- ✔ Zone Busy Status

Used With



VIPEDIA-12-NET

PAVA Audio router with network card

VIPEDIA-12-PRO

PAVA Audio router with network card - Dante Enabled



INTEGRA-PRO-03

PAVA Wall Mount System (3 amp channels pre installed) - Dante® Enabled



INTEGRA-PRO-05

PAVA Wall Mount System (5 amp channels pre installed) - Dante® Enabled



INTEGRA-PRO-07

PAVA Wall Mount System (7 amp channels pre installed) - Dante® Enabled



INTEGRA-PRO-10

PAVA Wall Mount System (10 amp channels pre installed) - Dante® Enabled



INTEGRA-03

Wall Mount PAVA System (3 amps)



INTEGRA-05

PAVA Wall Mount System (5 amp channels pre installed)



INTEGRA-07

PAVA Wall Mount System (7 amp channels pre installed)



INTEGRA-10

PAVA Wall Mount System
(10 amp channels pre
installed)



ANS04-ES

Wall Mount Sample and
Hold Ambient Noise Sensor