

1200300101

INTEGRA-PRO-10

PAVA Wall Mount System (10 amp channels pre installed) - Dante® Enabled

- EN 54-16 CERTIFIED
- SELF-CONTAINED WALL MOUNT PAVA SYSTEM
- SIMPLE INSTALLATION WITH MOUNTING FOR BATTERIES
- PRE-INSTALLED WITH 10 AMPLIFIER CHANNELS, EACH CAPABLE OF UP TO 500W @100V
- UP TO A TOTAL, 2000W @ 100V PER INTEGRA
- DANTE® ENABLED
- HIGH QUALITY PROFESSIONAL AUDIO PROCESSING
- 24 BIT 48 kHz AUDIO PROCESSING
- 12 ANALOGUE AUDIO INPUTS & OUTPUTS / 6 IP AUDIO INPUTS
- ON BOARD GENERAL PURPOSE INPUTS & OUTPUTS
- FLEXIBLE CONTROL OPTIONS
- INTEROPERABILITY WITH THE VIPEDIA RANGE

Public Address | Voice Alarm | Commercial Audio | Dante | Civil Defence Approval | EN54 EN 54 Certified

Description

The INTEGRA-PRO-10 all-in-one network enabled voice alarm solution is available with ten channels of pre-installed amplification.

The unit has 12 audio inputs and internal storage for up to 64 recorded messages. With a maximum power of 2000W, integrated audio-over-IP networking, powerful audio processing, and integrated battery charger and battery mounting shelf all in a compact wall-mount enclosure, INTEGRA provides a complete voice alarm solution for both medium to large centralised and decentralised PAVA systems.

Up to 32 INTEGRA can be linked by IP to enable broadcasts from any location to any combination of zones in large decentralised systems. The network switch (NETWORK-SWITCH-LP01) forms a voice alarm compliant ring network topology and can be easily mounted inside the enclosure.

For specialist applications that require ultra-low latency networked audio Dante® maybe used in the presence of other IP traffic across ASL's SecureLoop network. However, Dante®'s true power is in scaling up into a multi-user, cross-platform solution. In this cross-platform scenario, Dante™ traffic can be easily segregated from ASL's SecureLoop traffic via dedicated ports. This provides peace of mind that Life Safety aspects of the system are not accessible over the open cross-platform network.

Any INTEGRA variant and the rack mount equivalent VIPEDIA range interoperate seamlessly.

Accessories

www.zenitel.com info@zenitel.com Last revision date: 2026-01-20 11:04

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

BMB01 from datasheet

BMB01

Din Rail Mount I/O Expansion Device

Item Number: 1200550030



NETWORK-SWITCH-LP01

PAVA Network Switch - Layer 2

Item Number: 1200571000

from site

D150

PAVA 150W Power Amplifier Module for the V2000 / INTEGRA


Item Number: 1200202150

from site

D500

PAVA 500W Power Amplifier Module for the V2000 / INTEGRA

Item Number: 1200202500



LSZDC

PAVA Amplifier Interface Module for the V2000 / INTEGRA

Item Number: 1200540000

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.