

loudspeaker

tbd

SPCR-C-06W-65-EN54

FLUSH MOUNT CEILING SPEAKER

- EN 54-24 CERTIFIED
- SIZE 6.5" (165 MM) CHASSIS
- HIGH QUALITY AUDIO FOR VOICE AND BACKGROUND MUSIC
- 6W / 100V
- FLUSH MOUNT CEILING SPEAKER
- FLUSH MAGNETIC FASTENING GRILLE
- EASY MOUNT CLAMPS
- PROTECTION IP21C
- IMPACT RESISTANT ABS
- CERAMIC TERMINALS



Public Address



Voice Alarm

Commercial Audio

EN54

EN 54 Certified

Description

The SPCR-C-06W-65-EN54 is a 6W 100V round frameless ceiling mount loudspeaker, which has a 6.5" (165mm) full-range chassis providing excellent sound quality with speech and background music, and which is certified to EN54-24. The speaker is fitted with a 100V transformer which has three power adjustment tappings of 6W, 3W, and 1.5W.

The SPCR-C-06W-65-EN54 has a powder coated metal chassis and grille, with the high quality finish giving good long-term protection and resistance to corrosion. The speaker is supplied with a rear fire dome, and its enclosure is ingress protection rated to IP21C. As standard the speaker is coloured to match RAL9016 'Traffic White', however the speakers can be supplied in any four-digit RAL or NCS colour, as a special order.

Quick connections using the ceramic connector and easy ceiling mounting is provided through the use of spring clamps, for use with a possible ceiling thickness of between 1mm and 45mm. The 100V loudspeaker line cabling is fed through rubber grommets in the fire dome and is connected to the speaker by means of the ceramic connectors. For additional reliability, a thermal fuse is provided, and the speaker chassis is damp-resistant.

The loudspeaker is optionally available with a DC blocking capacitor fitted, providing compatibility with DC loudspeaker line monitoring systems. The part number for this DC monitoring compatible version is SPCR-C-06W-65-EN54-DC

Used With

page 1/2



from site

D150

PAVA 150W Power Amplifier
Module for the V2000 /
INTEGRA

from site

D500

PAVA 500W Power Amplifier
Module for the V2000 /
INTEGRA

V2000

PAVA 2000W Power Amplifier
Mainframe (0 amps Pre
Installed)

page 2/2